

Linksys SPA-941



Телефоны Linksys могут рекомендоваться как наиболее удачные офисные телефоны.

Эти телефоны демонстрируют хорошее соотношение цена/качество, высокую надежность при частом использовании и наличие всех необходимых офисных функций.

Настройка всех телефонов линксис более или менее схожа.

Здесь показывается настройка телефона на примере модели SPA-941

Настройка Linksys SPA-941

1) Заходим в веб-интерфейс устройства. По умолчанию устройство находится в режиме DHCP клиент и получает адрес от роутера

2) Жмём admin login

SIPURA
technology, inc.

Sipura Telephone Configuration

[Admin Login](#) [basic](#) | [advanced](#)
[Personal Directory](#) [Call History](#)

Info **System** **User**

System Information

DHCP:	Enabled	Current IP:	192.168.40.44
Host Name:	SipuraSPA	Domain:	allo
Current Netmask:	255.255.255.0	Current Gateway:	192.168.40.1
Primary DNS:	192.168.4.20		
Secondary DNS:			

Product Information

Product Name:	SPA-941	Serial Number:	4KM00J803914
Software Version:	4.1.8	Hardware Version:	1.0.4(3825)
MAC Address:	000E08D96766	Client Certificate:	Installed

Phone Status

Current Time:	4/22/2013 00:24:52	Elapsed Time:	2 days and 23:55:53
Broadcast Pkts Sent:	2	Broadcast Bytes Sent:	684
Broadcast Pkts Recv:	130495	Broadcast Bytes Recv:	10153851
Broadcast Pkts Dropped:	0	Broadcast Bytes Dropped:	0
RTP Packets Sent:	24245	RTP Bytes Sent:	3879200
RTP Packets Recv:	24464	RTP Bytes Recv:	3914240
SIP Messages Sent:	2234	SIP Bytes Sent:	1396059
SIP Messages Recv:	4426	SIP Bytes Recv:	1544306

3) Переходим в меню Ext1

Info **System** **SIP** **Regional** **Phone** **Ext 1** **Ext 2** **User**

[User Login](#) [basic](#) | [advanced](#)
[Personal Directory](#) [Call History](#)

4) Вводим логин и пароль для авторизации на sip.alloincognito.ru

SIPURA
technology, inc.

Sipura Telephone Configuration

Info System SIP Regional Phone **Ext 1** Ext 2 User [User Login](#) [basic](#) | [advanced](#)
[Personal Directory](#) [Call History](#)

General
Line Enable: yes ☐

NAT Settings
NAT Mapping Enable: no ☐ NAT Keep Alive Enable: no ☐

IP Settings
IP Port: 5060 SIP Debug Option: none ☐

Call Feature Settings
Message Waiting: no ☐ Default Ring: 5 ☐
Mailbox ID:

Proxy and Registration
Proxy: sip.alloincognito.ru ☐ Register: yes ☐
Take Call Without Reg: no ☐ Register Expires: 1200
Ans Call Without Reg: no ☐

Subscriber Information
Display Name: 0050000000 User ID: 0050000000
Password: ***** Use Auth ID: yes ☐
Auth ID: 0050000000

Audio Configuration
Preferred Codec: G711u ☐ Use Pref Codec Only: no ☐

5) Проверяем статус регистрации в меню info.

EXT 1 STATUS

Registration State:	Registered	Last Registration At:	4/22/2013 00:30:35
Next Registration In:	46 s	Message Waiting:	No
Mapped SIP Port:			